



General Overview

- **Chemistry of the Cells**
Lithium Iron Phosphate (LFP)
- **Capacity of the Pack**
3 KWh
- **No. of Modules in the Pack**
1 Module
- **No. of Cells in Each Module**
150 Cells
- **Total no. of Cells in Series**
15 Cells
- **Total no. of Cells in Parallel**
10 cells
- **Balancing Type in the Module BMS**
Active balancing
- **Balancing Current**
80 ± 10 mA
- **SOC Protection Level**
≤ 10%
- **Cell Voltage Rating**
3.2 V 6300 mAh
- **Nominal Voltage of Pack**
48 V
- **Minimum Voltage of Pack**
39 V
- **Maximum Voltage**
54.45 V
- **Rack Charging Profile**
NA
- **Continuous Charging Current 2**
20 Amps
- **Continuous Discharging Current**
60 Amps
- **Weight of Battery (~)**
30 Kgs
- **Weight Per KWH (~)**
10 Kgs
- **Volume**
As per casing (in Cubic Feet)
- **Form Factor and Dimensions**
As per casing

Charger

Parameter	Protection Values	Delayed	Protection and Relief Condition
Over Charge Voltage Protection	3.65 V	1-2 Sec	<ul style="list-style-type: none"> Discharge current The voltage drop to 3.5V
Over Charge Voltage Protection Level 1 (cell)	3.7 V	1-2 Sec	<ul style="list-style-type: none"> Discharge current The voltage drop to 3.5V
Over Charge Voltage Protection Level 2 (cell)	3.75 V	1 Sec	<ul style="list-style-type: none"> BMS Circuit breaker trips and need to reset manually
Over Charge Voltage Protection (Battery)	54.75 V	1-2 Sec	<ul style="list-style-type: none"> Discharge current The voltage drop to 52.5 V
Over Charge Voltage Protection Level 1 (Battery)	55.5 V	1-2 Sec	<ul style="list-style-type: none"> Discharge current
Over Charge Voltage Protection level 2 (Battery)	56.25 V	1 Sec	<ul style="list-style-type: none"> BMS Circuit breaker trips, and need to reset manually
Charge Over Current Protection Level 1	24 Amp	1-2 Sec	<ul style="list-style-type: none"> Discharge current
Charge Over Current Protection Level 2	26 Amp	1-2 Sec	<ul style="list-style-type: none"> Discharge current Reclose after 30 Sec delay. Over current after 3 consecutive times, report the fault and take it off-line

Discharge

Parameter	Protection Values	Delayed	Protection and Relief Condition
Over Discharge Voltage Protection (Cell)	2.5 V	1-2 Sec	<ul style="list-style-type: none"> All cell voltage rise to 2.8 V
Over Discharge Protection Voltage level 1 (Cell)	2.45 V	1-2 Sec	<ul style="list-style-type: none"> All cell voltage rise to 2.8 V Charge the current
Over Discharge Protection Voltage level 2 (Cell)	2.4 V	1 Sec	<ul style="list-style-type: none"> BMS Circuit breaker trips, and need to reset manually
Discharge Over Current Protection (Battery)	66 Amp	1-2 Sec	<ul style="list-style-type: none"> Reduce discharge current to less than the normal value
Discharging Over Current Protection level 1	72 Amp	1 Sec	<ul style="list-style-type: none"> Reclose after 30 Sec delay. Over current after 3 consecutive times, report the fault and take it off-line
Discharging Over Current Protection level 2 protection	78 Amp	3 Sec	<ul style="list-style-type: none"> BMS Circuit breaker trips, and need to reset manually
Short Current Protection	192 Amp	10 mS Tripping	<ul style="list-style-type: none"> BMS Circuit breaker trips, and need to reset manually

Charging Temperature Protection

Parameter	Protection Values	Delayed	Protection and Relief Condition
Charging High Temperature Protection	> 45 °C	1-2 Sec	<ul style="list-style-type: none">All temperature are below 45°C
Charging High Temperature Protection Level 1	> 50 °C	1-2 Sec	<ul style="list-style-type: none">All temperature are below 50°C
Charging High Temperature Protection Level 2	> 60 °C	10 Sec	<ul style="list-style-type: none">Circuit breaker trips, and need to reset manually
Charging Low Temperature Protection	> 0 °C	1-2 Sec	<ul style="list-style-type: none">All temperature are above 0°C
Charging Low Temperature Protection level 1	> -3 °C	1-2 Sec	<ul style="list-style-type: none">All temperature are above 0°C
Charging Low Temperature Protection level 2	> -5 °C	10 Sec	<ul style="list-style-type: none">Circuit breaker trips, & need to reset manually

Discharge Temperature Protection

Parameter	Protection Values	Delayed	Protection and Relief Condition
Discharge High Temperature Protection	> 55 °C	1-2 Sec	
Discharge High Temperature Protection Level 1	> 60 °C	1-2 Sec	
Discharge High Temperature Protection Level 2	> 65 °C	1 Sec	
Discharge Low Temperature Protection	> -5 °C	1-2 Sec	
Discharge Low Temperature Protection Level 1	> -10 °C	1-2 Sec	
Discharge Low Temperature Protection Level 2	> -15 °C	1 Sec	

Cell Balancing

The maximum cell voltage > 3.5V and the voltage difference > 40mV
The cell voltage > 3.65V

Voltage difference <= 20 mV

Operative Environmental Requirements (Recommended)

Parameter	Protection and Relief Condition
Charging operative temperature	0 ~ + 35°C
Discharging operative temperature	0 ~ + 45°C
Operating humidity range	<90 (40° C ± 2° C) %RH
Storage temperature range	0 ~ + 35°C
Storage humidity range	<90 (40° C ± 2° C) %RH



Born out of Innovation at IIT Hyderabad, PURE is committed to drive the future of e-mobility and ESS. We design and manufacture EV 2W and Lithium Batteries.

PURE Energy Private Limited
H No. 10 -38/2, Survey No. 424/AA3, Kandi Village Sangareddy,
Telangana - 5002285.

• **Write to us on:**
connect@pureenergy.co.in

• **Contact Us:**
6128477762 / 8328232960

• **Follow Us At:**
@purevindia



• **Connect With Us:**



*All product, product specifications and data are subject to change without notice to improve reliability, function or design or otherwise.